

# An application note for stocking and handling requirements of press pack devices and pressure contacted modules

## Stocking and handling requirements

IXYS UK Westcode recommends that devices and assemblies be stocked in their original packaging if possible. The devices and assemblies should be stored within the temperature range specified in the data sheet. Storage in conditions of very high humidity of greater than 95%RH for long periods should be avoided. The primary pack boxes should not be stacked more than five boxes high.

Press pack devices, assemblies and pressure contacted modules can be stored indefinitely as long as the storage conditions are within the limits specified in the datasheet. Pressure contact devices do not deteriorate with time.

Care should be taken in handling the devices and assemblies; in particular damage to the following should be avoided:

- Scratches and dents to the external anode and cathode contact faces of the device may result in reduced thermal and electrical performance.
- Mechanical damage to the device flanges, which may result in loss of hermetic sealing and a possible reduction in the useful life of the device.
- Cracking or chipping of the alumina ceramic which may result in loss of hermetic sealing or a reduction in tracking performance between the anode and cathode.
- Distortion to the end plates, bus bars and coolers of an assembly, which may result in water leaks, poor thermal performance or the inability to mount the stack to the assembly fixtures.
- Scratches or fingerprints on the assembly components that could damage the surface passivation and result and increase in localised oxidation or corrosion.
- Damage to assemblies resulting from multiple stacking.

**It is recommended that latex, vinyl or nitrile gloves be worn when handling devices or assemblies.**

Assemblies utilising oil filled capacitors should be orientated to prevent oil leaking from the capacitor.

The recommended manual handling procedures should be adopted when handling a number of devices or an assembly to avoid potential personal injuries. For an assembly, a crane or other suitable handling equipment is recommended.

**IXYS Semiconductor GmbH**  
Edisonstraße 15  
D-68623 Lampertheim  
Tel: +49 6206 503-0  
Fax: +49 6206 503-627  
E-mail: [marcom@ixys.de](mailto:marcom@ixys.de)



**IXYS UK Westcode Ltd**  
Langley Park Way, Langley Park,  
Chippenham, Wiltshire, SN15 1GE.  
Tel: +44 (0) 1249 444524  
Fax: +44 (0) 1249 659448  
E-mail: [sales@ixysuk.com](mailto:sales@ixysuk.com)

**IXYS Corporation**  
1590 Buckeye Drive  
Milpitas CA 95035-7418 USA  
Tel: +1 (408) 457 9000  
Fax: +1 (408) 496 0670  
E-mail: [sales@ixys.net](mailto:sales@ixys.net)

[www.ixysuk.com](http://www.ixysuk.com)

[www.ixys.com](http://www.ixys.com)

**IXYS Long Beach**  
2500 Mira Mar Avenue  
Long Beach CA 90815 USA  
Tel: +1 (562) 296 6584  
Fax: +1 (562) 296 6585  
E-mail: [service@ixyslongbeach.com](mailto:service@ixyslongbeach.com)

The information contained herein is protected by Copyright. And may not be used, copied, stored or disclosed except with the written permission of and in the manner permitted by the proprietors IXYS UK Westcode Ltd.

© IXYS UK Westcode Ltd.

In the interest of product improvement, IXYS UK Westcode reserves the right to change specifications or application notes at any time without prior notice.

**Important Notice:**

This document is provided by Littelfuse, Inc. ("Littelfuse") for informational and guideline purposes only. Littelfuse assumes no liability for errors or omissions in this document or for any of the information contained herein. Information is provided on an "as is" and "with all faults" basis for evaluation purposes only. Applications described are for illustrative purposes only and Littelfuse makes no representation that such applications will be suitable for the customer's specific use without further testing or modification. Littelfuse expressly disclaims all warranties, whether express, implied or statutory, including but not limited to the implied warranties of merchantability and fitness for a particular purpose, and non-infringement. It is the customer's sole responsibility to determine suitability for a particular system or use based on their own performance criteria, conditions, specific application, compatibility with other components, and environmental conditions. Customers must independently provide appropriate design and operating safeguards to minimize any risks associated with their applications and products.

LITTELFUSE PRODUCTS ARE NOT DESIGNED FOR, AND SHALL NOT BE USED FOR, ANY PURPOSE (INCLUDING, WITHOUT LIMITATION, AUTOMOTIVE, MILITARY, AEROSPACE, MEDICAL, LIFE-SAVING, LIFE-SUSTAINING OR NUCLEAR FACILITY APPLICATIONS, DEVICES INTENDED FOR SURGICAL IMPLANT INTO THE BODY, OR ANY OTHER APPLICATION IN WHICH THE FAILURE OR LACK OF DESIRED OPERATION OF THE PRODUCT MAY RESULT IN PERSONAL INJURY, DEATH, OR PROPERTY DAMAGE) OTHER THAN THOSE EXPRESSLY SET FORTH IN APPLICABLE LITTELFUSE PRODUCT DOCUMENTATION. WARRANTIES GRANTED BY LITTELFUSE SHALL BE DEEMED VOID FOR PRODUCTS USED FOR ANY PURPOSE NOT EXPRESSLY SET FORTH IN APPLICABLE LITTELFUSE DOCUMENTATION. LITTELFUSE SHALL NOT BE LIABLE FOR ANY CLAIMS OR DAMAGES ARISING OUT OF PRODUCTS USED IN APPLICATIONS NOT EXPRESSLY INTENDED BY LITTELFUSE AS SET FORTH IN APPLICABLE LITTELFUSE DOCUMENTATION.