

# POWR-GARD® Fuse Datasheet

## Box Cover Units



### Description

Provide economical method of protecting small motors against overcurrent damage.

### Applications

- Edison-Base plug fuses (TOO, TLO)
- Type S plug fuses (SOO, SLO) with adapters (SAO)

### Specifications

|                            |                                 |
|----------------------------|---------------------------------|
| <b>Voltage Rating</b>      | 125 V                           |
| <b>Max Amperage Rating</b> | 15 A                            |
| <b>Approvals</b>           | UL Listed parts (Except LSSYRL) |

### Web Resources

Sample requests, downloadable CAD drawings and other technical information: [www.littelfuse.com/boxcover](http://www.littelfuse.com/boxcover)




Figure 1




Figure 2




Figure 3




Figure 4




Figure 5




Figure 6




Figure 7

# POWR-GARD® Fuse Datasheet

## Box Cover Units

| FIGURE NUMBER | LITTELFUSE PART NUMBER | BOX COVER FEATURES      |                      |                    |                 |             | TO BE MOUNTED ON  |
|---------------|------------------------|-------------------------|----------------------|--------------------|-----------------|-------------|-------------------|
|               |                        | EDISON BASE FUSE HOLDER | GROUNDING RECEPTACLE | SINGLE POLE SWITCH | TWO POLE SWITCH | PILOT LIGHT |                   |
| 1             | LSOU                   | 1                       | —                    | —                  | —               | —           | 2-1/4" Handy Box  |
| 2             | LSRU*                  | 1                       | 1                    | —                  | —               | —           | 2-1/4" Handy Box  |
|               | LSRW                   | 1                       | 1                    | —                  | —               | —           | 2-3/4" Switch Box |
|               | LSRY                   | 1                       | 1                    | —                  | —               | —           | 4" Square Box     |
| 3             | LSSU*                  | 1                       | —                    | 1                  | —               | —           | 2-1/4" Handy Box  |
|               | LSSW                   | 1                       | —                    | 1                  | —               | —           | 2-3/4" Switch Box |
|               | LSSY*                  | 1                       | —                    | 1                  | —               | —           | 4" Square Box     |
| 4             | LSOYB                  | 2                       | —                    | —                  | —               | —           | 4" Square Box     |
| 5             | LSSYRL                 | 1                       | 1                    | 1                  | —               | 1           | 4" Square Box     |
| 6             | LSCY                   | 2                       | —                    | 2                  | —               | —           | 4" Square Box     |
| 7             | LSTY                   | 2                       | —                    | —                  | 1               | —           | 4" Square Box     |

\*UL Listed (File No. E308725)

**Disclaimer Notice** – Information furnished is believed to be accurate and reliable. However, users should independently evaluate the suitability of and test each product selected for their own applications. Littelfuse products are not designed for, and may not be used in, all applications. Read complete Disclaimer Notice at [www.littelfuse.com/product-disclaimer](http://www.littelfuse.com/product-disclaimer).