

Military Midget 10x38 mm Fuses

593 Series

Commercial Equivalent = [FLM Series](#)



Description

With a vast network of manufacturing and engineering facilities and a global system of distribution channels, Littelfuse offers a variety of switchgear fuses to meet your specific needs, including military high-reliability fuses.

Features & Benefits

FEATURES	BENEFITS
10x38 mm size	Common dimensions used in a variety of applications
Time-delay	Allows for temporary current surge for a short period of time without blowing
Fiberglass body	Cost effective materials provide a lower cost alternative for supplemental circuit protection
POWR-GARD® technology	Ensures quality overcurrent protection

Applications

- Control circuits transformers
- Solenoids
- Circuits with high in-rush currents
- Small motors

Approved to MIL-PRF-15160

MIL TYPE DESIGNATION	NICKEL-PLATED CAPS
F09B 250V 3/10A	593.300
F09B 250V 4/10A	593.400
F09B 250V 1/2A	593.500
F09B 250V 6/10A	593.600
F09B 250V 8/10A	593.800
F09B 250V 1A	593.001
F09B 250V 1 1/8A	593.1.12
F09B 250V 1 1/4A	593.1.25
F09B 250V 1 3/10A	593.01.4
F09B 250V 1 1/2A	593.01.5

Military Midget 10x38 mm Fuses

593 Series

Approved to MIL-PRF-15160

MIL TYPE DESIGNATION	NICKEL-PLATED CAPS
F09B 250V 1 $\frac{1}{10}$ A	593 01.6
F09B 250V 1 $\frac{1}{10}$ A	593 01.8
F09B 250V 2A	593 002
F09B 250V 2 $\frac{1}{4}$ A	593 2.25
F09B 250V 2 $\frac{1}{2}$ A	593 02.5
F09B 250V 2 $\frac{3}{10}$ A	593 02.8
F09B 250V 3A	593 003
F09B 250V 3 $\frac{3}{10}$ A	593 03.2
F09B 250V 3 $\frac{1}{2}$ A	593 03.5
F09B 250V 4A	593 004
F09B 250V 4 $\frac{1}{2}$ A	593 04.5
F09B 250V 5A	593 005
F09B 250V 5 $\frac{1}{10}$ A	593 05.6
F09B 250V 6A	593 006
F09B 250V 6 $\frac{1}{4}$ A	593 6.25
F09B 250V 7A	593 007
F09B 250V 8A	593 008
F09B 250V 9A	593 009
F09B 250V 10A	593 010
F09B 125V 12A	593 012
F09B 125V 15A	593 015
F09B 32V 20A	593 020
F09B 32V 25A	593 025
F09B 32V 30A	593 030

Note: Boldface numbers indicate series; light type numbers indicate amperage value.

Disclaimer Notice – Information furnished is believed to be accurate and reliable. However, users should independently evaluate the suitability of and test each product selected for their own applications. Littelfuse products are not designed for, and may not be used in, all applications. Read complete Disclaimer Notice at www.littelfuse.com/product-disclaimer.